

## OA300

### Manual Call Point (Conventional)



#### Product Overview

---

The OA300 Manual Call Point is used to manually transmit fire alarm signal, it provides contact closure to activate emergency equipment, audible and visual signals, and alarm panels. It is generally installed in staircase, hallway, evacuation passage or places where people haunt.

#### Characteristics

---

- Integrated with on-and-off input signal
- Sending signal to Intelligent Monitoring Modular for processing or activate the fire bell and other fire protection equipment
- Test key included
- Simple structure
- Dual wiring terminals
- Easy installation and wiring
- Comply with Standard: GB19880-2005

#### Specifications

---

Operating Voltage: DC24V / AC220V    Standby Current: 0 mA    Maxim Current:  $\leq 5$  A

Contact Capacity: DC24V/1A    Contactor Resistance:  $\leq 0.1$  ohm

Operating Environment: Temperature:  $-10^{\circ}$  C~ $+50^{\circ}$  C

Related Humidity:  $\leq 95\%$  ( $40 \pm 2^{\circ}$  C)

Dimensions: 86×86×52mm (length × width × height)    Weight 165g

#### Orena Sales and Service

---

##### Shenzhen Orena Photonic Technology Co., Ltd

Orena Bldg, Zhong'an Industrial Park, Longjing Road, Nanshan District, Shenzhen, 518055, P.R.China

Ph: 86.755.8623.3886    86.755.2678.7499    Fx: 86.755.2678.7499

E-mail: oem@orena.com.cn

www.orena.com.cn